

调速电动机 Speed Control Motors

60W

□90mm



规格Specs 连续额定Cont. Rated

型号Model·类型Type 导线型Wire Type		最大输出功率 Output Power W	电压 Voltage V	频率 Frequency Hz	调速范围 Speed Control Range r/min	容许转矩 Allowance Torque		启动转矩 Starting Torque mN.m	电流 Current A	电容器容量 Capacitor μF
齿轮轴型 Pinion Shaft	圆轴型 Round Shaft					1200r/min mN.m	90r/min mN.m			
5IK60RGN-AFJ	5IK60RA-AFJ	60	1ph100	50	90~1400	460	140	265	2.00	20.0
				60	90~1700	490	160			
5IK60RGN-EFJ	5IK60RA-EFJ	60	1ph110	60	90~1700	490	160	265	1.80	12.0
			1ph120							
5IK60RGN-CFE	5IK60RA-CFE	60	1ph220	50	90~1400	490	140	265	0.80	4.0
			1ph230							
5IK60RGN-HFE	5IK60RA-HFE	60	1ph220	60	90~1700	490	160	265	0.85	
			1ph230							

- 电动机铭牌上的型号并无表示电容器种类的(J、E)记号。
With the name on record on the motor nameplate, there is no capacitor types(J、E) marked.
- 各种安全规格以电动机铭牌上的型号取得认证。
When the motor is approved under various safety standards, the model name on the nameplate is the approved model name.

种类/Type

电动机/Motor

机型 Type	型号Model	
	齿轮轴型 Pinion Shaft	圆轴型 Round Shaft
导线型 Lead Wire Type	5IK60RGN-AFJ	5IK60RA-AFJ
	5IK60RGN-EFJ	5IK60RA-EFJ
	5IK60RGN-CFE	5IK60RA-CFE
	5IK60RGN-HFE	5IK60RA-HFE

平行轴减速器(另售)/
Parallel Shaft Gearhead (Sold Separately)

减速器种类 Gearhead Type	减速器型号 Gearhead Model	减速比Gear Ratio
长寿命·低噪音 Long Life·Low Noise	5GN□K	3、3.6、5、6、7.5、9、 12.5、15、18、25、30、 36、50、60、75、90、 100、120、150、180、200
	5GN10XK (中间减速器Decimal gearhead)	

- 减速器型号的□中为减速比的数值
Enter the gear ratio in the box (□) within the model name